

## Pro-Ject Pre Box

Pre-amplifier with remote control



### Good sound from sound technology

- Metal case shields the electronics from vibrational and electromagnetic interference
- Optimal channel separation through dual-mono circuitry
- Special low-noise ICs used
- Gold plated RCA connection sockets
- Outboard power supply included

### Features

- Remote controllable
- Small size allows easy placement
- Optional input expander Pro-Ject Switch Box providing four additional inputs. Automatic synchronization with the input selector of the Pro-Ject Pre Box.
- Remote power switching for connected units via on/off switch (Trigger Pre)

### Technical specifications

Frequency response:	20Hz - 20kHz (+ - 0,2 dB)
Noise floor:	-100dB (A weighted)
THD:	0,001%
Gain:	8,5dB
Pre out:	1 pair RCA/Phono sockets
Output voltage typically:	1V at 1kHz
Line-level inputs:	2 pairs RCA/Phono sockets
Input impedance:	20kohms
Trigger:	12V DC switching voltage
Trigger Amp:	2-pole 2,5mm co-axial jack
Outboard power supply:	16V/500mA AC, suitable for your country's mains supply
Power consumption:	16V/200mA AC
Dimension W x H x D:	103 x 76 x 141mm
Weight:	630g without power supply

The manufacturer reserves the right to alter the technical specifications without notice.



Available in silver or black finish